



○ GENSET MODEL

	Prime	JGP150P1	
	Standby	JGP165E1	
Engine speed	rpm	1500	1800
Frequency	Hz	50	60
Prime Power	KVA	150	N/A
	KW	120	N/A
Standby Power	KVA	165	N/A
	KW	132	N/A
Gross Engine Power	KW	151	N/A
	hp	202	N/A

*Rating at 0.8 Power Factor

Fuel Consumption @ 50% load	L/hr	17.4	N/A
@ 75% load	L/hr	26.4	N/A
@ 100% load	L/hr	31.2	N/A

○ TECHNICAL DATA

Perkins Engine Model	1006TAG2		
Leroy Somer / Stamford Alternator Model	LSA44.2M95 / UCI274F		
Number of Cylinders	6 in line		
Cubic Capacity	Litres	6	
	cu.in	366	
Bore	mm	100	
	in	3.94	
Stroke	mm	127	
	in	5	
Fuel Tank Capacity	Lit	275	

○ DIMENSIONS & WEIGHT

Length	cm	270
Width	cm	90
Height	cm	147
Weight	Kg	1535

Prime Rating: These ratings are applicable for supplying continuous electrical power in lieu of commercially purchased power. This model can supply 10% overload power for 1 hour in 12 hours.

Standby Rating: These ratings are applicable for supplying continuous electrical power in the event of utility power failure. No overload is permitted on these ratings.



Rua Pedro de Castro vandunen (Loy) entre a retunda de entrada do Nova Vida e a entrada do Gamek, Kilamba Kiayi

Fax: 222 383 187
Tel: 912 503 137
923 320 418
923 343 142

E-Mail: beledear@gmail.com
Web: www.beledear.com