



○ GENSET MODEL

	Prime	JGP250H2	
	Standby	JGP275E2	
Engine speed	rpm	1500	1800
Frequency	Hz	50	60
Prime Power	KVA	250	N/A
	KW	200	N/A
Standby Power	KVA	275	N/A
	KW	220	N/A
Gross Engine Power	KW	250.9	N/A
	hp	336	N/A

\*Rating at 0.8 Power Factor

Fuel Consumption @	50% load	L/hr	31.1	N/A
	75% load	L/hr	46.1	N/A
	100% load	L/hr	58.9	N/A

○ TECHNICAL DATA

Perkins Engine Model	1306C-E87TAG6		
Leroy Somer / Stamford Alternator Model	LSA46.2L6 / UCD274K		
Number of Cylinders	6 in line		
Cubic Capacity	Litres	8.7	
	cu.in	531	
Bore	mm	116.6	
	in	4.6	
Stroke	mm	136	
	in	5.4	
Fuel Tank Capacity	Lit	385	

○ DIMENSIONS & WEIGHT

Length	cm	290
Width	cm	99
Height	cm	170
Weight	Kg	2252

Prime Rating: These ratings are applicable for supplying continuous electrical power in lieu of commercially purchased power. This model can supply 10% overload power for 1 hour in 12 hours.

Standby Rating: These ratings are applicable for supplying continuous electrical power in the event of utility power failure. No overload is permitted on these ratings.



Rua Pedro de Castro vandunen (Loy) entre a retunda de entrada do Nova Vida e a entrada do Gamek, Kilamba Kixi

Fax: 222 383 187  
Tel: 912 503 137  
923 320 418  
923 343 142

E-Mail: [nabil06@hotmail.com](mailto:nabil06@hotmail.com)  
[www.beledear.com](http://www.beledear.com)