



○ GENSET MODEL

	Prime	JGP27P1	
	Standby	JGP30E1	
Engine speed	rpm	1500	1800
Frequency	Hz	50	60
Prime Power	KVA	27	30
	KW	21.6	24
Standby Power	KVA	30	34
	KW	24	27.2
Gross Engine Power	KW	31	36.5
	hp	42	49

*Rating at 0.8 Power Factor

Fuel Consumption @	50% load	L/hr	3.6	4.4
	75% load	L/hr	4.8	5.7
	100% load	L/hr	6.2	7.2

○ TECHNICAL DATA

Perkins Engine Model	1103A - 33G1		
Leroy Somer / Stamford Alternator Model	LSA42.2M7 / BCI 184F		
Number of Cylinders	3 in line		
Cubic Capacity	Litres	3.3	
	cu.in	201.4	
Bore	mm	105	
	in	4.1	
Stroke	mm	127	
	in	5	
Fuel Tank Capacity	Lit	103	

○ DIMENSIONS & WEIGHT

Length	cm	165
Width	cm	73
Height	cm	124
Weight	Kg	800

Prime Rating: These ratings are applicable for supplying continuous electrical power in lieu of commercially purchased power. This model can supply 10% overload power for 1 hour in 12 hours.

Standby Rating: These ratings are applicable for supplying continuous electrical power in the event of utility power failure. No overload is permitted on these ratings.



Rua Pedro de Castro vandunen (Loy) entre a retunda de entrada do Nova Vida e a entrada do Gamek, Kilamba Kiayi

Fax: 222 383 187
Tel: 912 503 137
923 320 418
923 343 142

E-Mail: nabil06@hotmail.com
www.beledear.com